ADAM-6117 ADAM-6160

8-ch Isolated Analog Input Real-time Ethernet Module

6-ch Relay Real-time Ethernet Module

90000



ADAM-6117

FCC C€ ROHS

ADAM-6160EI

ADAM-6160

FCC CE ROHS

Specifications

Analog Input

 $\begin{array}{lll} \bullet & \textbf{Channels} & \textbf{8 (differential)} \\ \bullet & \textbf{Input Impedance} & > 10 \ \text{M}\Omega \ \text{(voltage)} \\ & 120 \ \Omega \ \text{(current)} \\ \end{array}$

■ Input Type mV, V, mA ■ Input Range ±150 mV, ±500 mV, ±1 V

±5 V, ±10 V, 0 ~ 20 mA, 4 ~ 20 mA, ±20 mA

 $\begin{array}{lll} \bullet & \textbf{Span Drift} & \pm 30 \ ppm/^{\circ} C \\ \bullet & \textbf{Zero Drift} & \pm 6 \ \mu V/^{\circ} C \\ \bullet & \textbf{Resolution} & 16-bit \end{array}$

■ Accuracy ± 0.1% of FSR (Current) at 25°C ± 0.2% of FSR (Current) at 25°C

Sampling Rate 10 sample/second (total)

CMR @ 50/60 Hz
NMR @ 50/60 Hz
High Common Mode
200 V_{DC}

Ordering Information

ADAM-6117EI
8-ch Isolated AI EtherNet/IP Module

Specifications

Relay Output

• Channels 5 Form C and 1 Form A

Contact Rating (Resistive) 250 V_{AC} @ 5A 30 V_{DC} @ 5A
Max. Switching Voltage 400 V_{AC} 300 V_{DC}

Breakdown Voltage 500 V_{AC} (50/60Hz)
Max. Breakdown 1250 VA Capacity

• Frequency of Operation 360 operations/hour with load 72,000 operations/hour without load

Set/Reset Time
Mechanical Endurance
Isolation between
8 ms/8 ms
> 15 x 10⁶ operations
1000 V_{rms}

Contact

■ Insulation Resistance $> 10~G\Omega @ 500~V_{DC}$

Ordering Information

ADAM-6160EI 6-ch Relay EtherNet/IP Module

Common Specifications

General

• LAN 10/100Base-T(X)

Power Consumption ADAM-6117: 3.5 W @ 24 V_{DC} ADAM-6160: 4.5 W @ 24 V_{DC}
Connectors 2 x RJ-45 LAN (Daisy Chain)

Plug-in screw terminal block (I/O and power)

Watchdog System (1.6 second)
Power Input 10 ~ 30 V_{DC}

Protection

Isolation Protection 2,500 V_{DC}
Built in TVS/ESD Protection

Power Reversal Protection

Environment

Operating Temperature
Storage Temperature
Operating Humidity
-20 ~ 95% RH (non-condensing)

■ **Storage Humidity** 0 ~ 95% RH (non-condensing)